

### Features

- Built-in 100v/70v transformer
- Wall mount type loudspeaker
- 5" full range speaker unit
- Power taps 0.75w-1.5w-3w-6w @100V
- Wooden enclosure and fabric mask in black

### Description

The T-601L is a wall mount speaker built-in 70v/100v transformer. The 70v/100v transformer technique reduces line losses on longer distance and allows easy parallel connection of multiple loudspeakers.

The built-in 5" full range speaker driver is designed of wide frequency response 100-16kHz, the multiple power taps 0.75W, 1.5W, 3W & 6W are helpful for different applications varies from room size and ambient noise surroundings.

The wooden enclosure and fabric mask are of black color. Easy and secure wall mount installation through the supplied mounting hook.




It is ideal choice for industrial and commercial applications in hotel, school, office and factory where background music and paging is needed.



### Specification

|                            |  |
|----------------------------|--|
| Model                      | T-601L   |
| Power Taps @100V           | 0.75W , 1.5W, 3W, 6W,  |
| Power Taps @70V            | 0.38W , 0.75W, 1.5W, 3W                                      |
| Impedance                  | Black:Com Green:1.7KΩ White:3.3KΩ Yellow:6.7 KΩ Blue:13.3 KΩ |
| SPL(1W/1M)                 | 92dB   |
| Max.SPL (Rated W/1M)       | 100dB  |
| Frequency Response (-10dB) | 100-16KHz  |
| Finish                     | Baffle: Wooden, Black Grille: Cloth, Black                   |
| Speaker Driver             | 5" x1  |
| Dimensions                 | 200x105x250mm  |
| Weight                     | 1.9Kg  |
| Mounting                   | Hook   |

**Appearance:**



**Frequency Response**

