

T-6S/T-23S/T-26S/T-212S/T-2200S/T-6FS/T-23FS/T-26FS/T-212FS/T-2200FS (With separated toroidal transformer)



Plastic box



Metal box

Specifications

Model	T-6S	T-23S	T-26S	T-212S	T-2200S	T-6FS	T-23FS	T-26FS	T-212FS	T-2200FS
Rated Power	6W	30W	60W	120W	200W	6W	30W	60W	120W	200W
Type	Resist	Trans 1	Trans 2	Trans 2	Trans 2	Resist	Trans 1	Trans 2	Trans 2	Trans 2
Steps	5	5	5	5	5	5	5	5	5	5
Wall Plate	Plastic									
24V Input	/	/	/	/	/	24V	24V	24V	24V	24V
Dimensions	82.5× 82.5× 45mm									
Trans 1 DIM	77× 77× 27mm									
Trans 2 DIM	74× 74× 27mm									

Attn:

1. T-6/T-6F/T-6S/T-6FS can use standard common plastic bottom box (L86× W86× H50mm) for installation, for other models, if do not use special metal box when installation, you has to fix the transformer in other position, and connect the down-lead to the volume control switch.

2. You have to use our special metal box (L82.5× W82.5× H80mm) If use special metal box when installation. Special bottom box you have to buy by yourself.

3. Model "F" with means 24V input

4. Model with "S" means program selection

